



## INTRODUCTION

Aksa Power Generation has been producing industrial generator sets with an innovative compact design and excellence in quality for over 30 years. Aksa has been providing reliable power through three main production plants and over 15 branch offices worldwide.

### Power (kVA)

60 Hz

VOLTAGE	PHASE	Pf	STANDBY RATING (ESP)		Standby Ampere	PRIME RATING (PRP)		Prime Ampere
			kW	kVA		kW	kVA	
240/120	1	1	50	50	208.3	45	45	187.5
208/120	3	0.8	55	68.75	190.8	50	62.5	173.4
480/277	3	0.8	55	68.75	82.7	50	62.5	75.1

**STANDBY POWER (Maximum)** Power available at variable load in the event of main power network failure. No over load is permitted.

**PRIME POWER** Power available at variable load in lieu of a main power network. Overload of 10% is permitted for 1 hour in every 12 hours of operation. The above ratings represent the engine performance capabilities to conditions specified in accordance with ISO 8528. Derating may be required for conditions outside of the test conditions.

## GENERAL CHARACTERISTICS

Model Name	APD-EPAJ55T4
Frequency (Hz)	60
Fuel Type	Diesel
Engine Make and Model	JOHN DEERE 4045HFG04-PWL ( <b>Tier-4</b> )
Alternator Make and Model	STAMFORD UCI224F
Control Panel Model	DSE 7320



### ENGINE SPECIFICATIONS

Engine	John Deere
Engine Model	4045HFG04-PWL
Number of Cylinder	4 cylinders - in line
Max. power @ rated rpm; kWm (BHP)	80 (107)
Brake mean effective pressure;	900 kpa @ prime
Aspiration & Cooling	Turbo Charged Air to Air After Cooled
Total displacement; in <sup>3</sup> (L)	4.5 (275)
Bore; in. (mm)	4.2 (106)
Stroke; in. (mm.)	5.0 (127)
Compression Ratio	17.0:1
Governor Type	ECU, ISO8528-G3
Rated rpm	1800
Rotation	Anti-clockwise viewed on flywheel

### ENGINE ELECTRICAL SYSTEM

Charging Alternator	12V, Negative Ground
Alternator Rating; (amp)	65
Starter motor power; (kW)	3.0
Starter motor rated voltage; (dc)	12
Battery quantity x rating & CCA	1 x 60Ah, 640

### FUEL SYSTEM

Type of injection	Direct
Fuel injection pump	Denso HP3
Fuel prime pump	Manual
Max. fuel flow; kg/hr (lb/hr)	39/86
Fuel filter & water separator	Available

### FUEL CONSUMPTION

110% Load (Standby) (gal/h)	4.4
100% Load (Prime) (gal/h)	4
75% Load (Prime) (gal/h)	3.1
50% Load (Prime) (gal/h)	2.3

### EXHAUST SYSTEM

Exhaust gas flow; (m3/min)	11.2
Max. back pressure; (kPa)	7.5
Max. exhaust gas temp in manifold; (°C)	380



### COOLING SYSTEM

Radiator ambient temp; °C (°F)	TBD
Coolant capacity; L (gal)	30
Thermostat operation range; °C	85-97
Combustion air flow; m <sup>3</sup> /min	5.3
Engine coolant flow; L/min (gal/min)	245
Cooling fan air flow;	152,61 m <sup>3</sup> /min
Max. restriction of radiator; kPa (in H <sub>2</sub> O)	0,363 (1,46)
Air filter	Paper Element

### LUBRICATION SYSTEM

Oil capacity; L (gal)	15 (3,96)
Oil cooler	Water cooled
Oil filter	Spin on, replaceable
Oil temp (continuous operation); °C	138

### ALTERNATOR CHARACTERISTICS

Manufacturer	Stamford
Model	UCI 224F - 60Hz
Design	4 Pole, drip proof rotating field
Exciter type	Self Excited
Stator	2/3 winding pitch
Rotor	Single bearing, flexible disc
Leads	12
Insulation	Class H
Temp. rise @ 40°C ambient	125°C Prime
Max. over-speed; rev/min	2250
Voltage regulator	AS440

### OPTIONAL 4 POSITION VSS (kW Rating at 1800rpm/60Hz)

480/277V - 3ph – 0.8pf	75.04 kW
240/120 3ph 208/120V - 3ph - 0.8pf	67.04 kW
240/120V - 1ph – 1pf	60 kW



## GEN.SET CANOPY DIMENSIONS

LENGTH (in)	124
WIDTH (in)	45.51
HEIGHT (in)	79.4
DRY WEIGHT (lb)	5258
FUEL TANK CAPACITY (gal)	100.4
GENSET SOUND LEVEL (dBA@23ft)	TBD



1. Steel structures.
2. Emergency stop push button.
3. Control panel is located at the rear side of the generator set.
4. Corrosion-resistant locks and hinges.
5. Oil could be drained via valve and a hose
6. Exhaust system in the canopy.
7. Special large access doors for easy maintenance
8. In front and back side special large access doors for easy maintenance
9. Base frame -fuel tank.
10. Lifting points similar to ISO container , located on each top corner of the canopy.
11. The cap on the canopy provides easy access to radiator cap.
12. Sound proofing materials

## BASE-FRAME ENCLOSURE

- The complete gen-set is mounted entirely on a heavy duty base frame with an integral double wall fuel tank.
- Anti vibration isolators are installed between engine/alternator supports and the base frame.
- All enclosure parts are designed with module principles without welding
- Enclosure has four doors on each side for easy serviceability and back door for control system.
- Exhaust silencer is protected (Coated) against environmental outdoor conditions and is internally mounted within enclosure.
- Exhaust pipe thermally insulated on engine compartment.
- All metal enclosure parts are painted by electrostatic polyester powder paint.
- Fuel filling cap is within the Enclosure, and reachable through lockable door.
- Emergency stop switch externally mounted on enclosure.
- Components installed in sheet steel enclosure.
- Phosphate chemical, pre-coating of steel provides corrosion resistant surface
- Polyester composite powder topcoat forms high gloss and extremely durable finish
- Lockable hinged panel door provides for easy component access

## CONTROL PANEL

Control Module	DSE
Control Module Model	DSE 7320
Communication Ports	MODBUS



1. Menu navigation buttons
2. Close mains button
3. Main Status and instrumentation display
4. Alarm LED's
5. Close generator button
6. Status LED's
7. Operation selecting buttons

Manufacturer reserves the right to make change in the model, technical specifications, color, equipment, accessories and images without prior notice. (12.03.2020)



## GENERATING SET CONTROL UNIT

The DSE 7320 includes the additional capability of being able to monitor a mains (utility) supply and is therefore suitable for controlling a standby generating set in conjunction with an automatic transfer switch.

The DSE7320 also indicates operational status and fault conditions, automatically shutting down the generating set and indicating faults by means of its LCD display on the front panel.

- UL recognized, NFPA110 Level 1 compatible
- LCD text display, key menu navigation and front panel editing
- Off/Manual/Auto model switch
- Two wire starting/stopping in Auto mode
- Engine exerciser
- IP65 front panel rating with supplied sealing gasket
- Configurable 8 inputs, 6 analogue inputs, 6 DC outputs with expansion capability
- Real time clock provides accurate event logging
- Fully configurable via DSE Configuration Suite PC software
- Remote SCADA monitoring and BMS integration features
- License free PC software

## STANDARD SPECIFICATIONS

Microprocessor controlled

- 132 x 64 pixel LCD display makes information easy to read
- Front panel programming and also via PC software
- Soft touch membrane keypad and five key menu navigation
- Remote communications via RS232, RS485 and ethernet.
- Event logging (50) showing date and time
- Multiple date and time engine exercise mode and maintenance scheduler
- Coolant heater control.
- Controls; stop, manuel, auto, test, start, mute lamb test/transfer to generator, transfer to mains, menu navigation.

## Instruments

### ENGINE

- Engine speed
- Oil pressure
- Coolant temperature
- Run time Battery volts
- Engine maintenance due

### MAINS

- Voltage (L-L, L-N)
- Frequency

### GENERATOR

- Voltage (L-L, L-N)
- Current (L1-L2-L3)
- Frequency
- Earth current
- kW
- Pf
- kVAr
- kWh, kVAh, kVArh
- Phase sequence

**PRE-ALARMS**

- Low oil pressure
- High engine temperature
- Low engine temperature
- Over /Under speed
- Under/over generator frequency
- Under/over generator voltage
- ECU warning

**ELECTRICAL TRIP**

- Earth fault
- kW over load
- Generator over current
- Negative phase sequence

**WARNING**

- Charge failure
- Battery under voltage
- Fail to stop
- Low fuel level (opt.)
- kW over load
- Negative phase sequence
- Loss of speed signal

**SHUT DOWNS**

- Fail to start
- Emergency stop
- Low oil pressure
- High engine temperature
- Low coolant level
- Over /Under speed
- Under/over generator frequency
- Under/over generator voltage
- Oil pressure sensor open
- Phase rotation

**Options**

- High oil temperature shut down
- Low fuel level shut down
- Low fuel level alarm
- High fuel level alarm
- EXPANSION MODULES
- Editional LED module (2548)
- Expansion relay module (2157)
- Expansion input module (2130)

**Standards**

- Electrical Safety / EMC compatibility
- BS EN 60950 Electrical business equipment
- BS EN 61000-6-2 EMC immunity standard
- BS EN 61000-6-4 EMC emission standard



## STANDARD SPECIFICATIONS

- **EPA Certified Tier 4 – FINAL** engine powered generator set for Mobile / Prime Applications.
- The Generator set is designed and manufactured in a facility certified to **ISO9001:2015** standards.
- **John Deere heavy duty** four cycle industrial diesel engine delivers low emission, reliable power, fuel efficiency and fast response to load changes.
- **Non-proprietary control system** provides total gen-set system integrated control, protections, metering, automatic starting/stopping with options of remote control, remote display or remote annunciation.
- **Aksa Power Generation** provides **single source responsibility** for the generator set & accessories.
- The generator set, with its components, are **prototype tested** and **production tested**.
- **Stamford** industrial generators meet the requirements of BS EN 60034 and the relevant sections of other international standards.
- **Heavy duty base frame** with integral pad **vibration isolators** eliminates the need for under unit spring vibration isolators.

### Convenience Panel Accessories

- (2) Two 20A, 120V GFCI receptacles and breakers
- (3) Three 50A, 240V twist lock receptacles and breakers
- 5-15A, 125V inlet receptacles for battery charger and water heater
- Two wire remote start station
- Generator set voltage adjust rheostat
- (5) 400A rated, stud type quick connect cam-locks

### Standard Features & Accessories

- Trailer w/spare tire and tool box
- Sound Attenuated Steel Enclosure
- Heavy Duty Steel Base-frame
- Exhaust system with Doc+SCR
- Flex Fuel Lines
- Oil Drain Valve & Extension
- Convenience Panel
- Voltage Selector Switch – 3 position
- Emergency Stop Switch
- Battery, Battery Rack & Cables
- Battery Charger (Input: 196-264V, Output: 27.6V 5A or 13.8V 5A)
- Main Line CB
- Jacket Water Heater (120 VAC, 1000 W)
- Operations Manual
- 1 Year / 2000 hours Limited Warranty

### Voltage Selector Switch

- Three positions at 480/277V, 208/120V - 3ph & 240/120 - 1ph
- Product of Salzer or Kraus&Naimer

### Trailer

- DOT approved 10,000lbs heavy duty dual axle trailer
- Spring axles w/electric brakes
- Breakaway kit with charger
- 5000lbs front jack and rear stabilizer jacks
- 7 pin trailer plug
- Tool box and spare tire

### Circuit Breaker

- 250Amp capacity main line circuit breaker
- Shunt trip controller by generator set control



## OPTIONAL ACCESSORIES

- Upsized Alternator
- PMG Excitation
- Alternator Anti-condensation Heater
- 4 Position VSS
- Fuel Level Monitoring on Controller & High Fuel Alarm
- Fuel Line Check Valve
- Oil Temperature Gauge
- Oil Heater
- Battery Charger 10Amp
- Battery Heater Blanket
- Main Line CB (100% rated)
- Remote Monitoring and Control
- Remote Annunciator

## AKSA CERTIFICATES

- TS ISO 8528
- CE
- SZUTEST
- 2000/14/EC

**AKSA POWER GENERATION USA LLC**  
371 Exchange Street, West Monroe,  
Louisiana, 71292  
T: +1 318 855 83 77 F: +1 318 855 83 81  
e-mail: sales@aksausa.com

**DISTRIBUTED BY:**